

## [Feature]

- One set of conversion port: RS485/422 to USB converter



## [Specification]

|                     |                                            |                           |
|---------------------|--------------------------------------------|---------------------------|
| Power supply        | USB Bus Power (5V) ◆Power consumption : 1W |                           |
| Environment         | Operating temperature                      | 0~60°C                    |
|                     | Storage temperature                        | -20~85°C                  |
|                     | Humidity                                   | 5~95%RH                   |
| Signal conversion   | Baud rate                                  | 300~230.4kbps ·           |
|                     | Conversion port                            | 1 set                     |
|                     | RS-422                                     | RxD+ · RxD- · TxD+ · TxD- |
|                     | RS-485                                     | Data+ · Data -            |
|                     | RS-422, RS-485 automatic detection         |                           |
|                     | Receive buffer                             | 576 bytes                 |
|                     | Transmit buffer                            | 640 bytes                 |
| Physical conditions | Product dimensions (mm)                    | 55x40x25 (W× L× H )       |
|                     | Product weight                             | 35g                       |
| Driver support      | Windows-7 、 8 、 10/Mac osxux2.4/2.6        |                           |